## STATE BANK OF INDIA SCHEDULE OF WORKS: ELECTRICAL WORKS

NEW GODOWN BRANCH RBO GAYA

NO.	DESCRIPTION ELECTRICAL	UNIT	QTY	RATE	AMOUNT
	MAIN INCOMING SOURCE PANEL (MISP):  Supply, installation, testing and commissioning of main incoming (MIP) Panel suitable for wall /floor mounted indoor type, air insulated, totally enclosed vermin-proof (IP 42), dead front, cubicle type, 2 mm thick sheet steel enclosure use on 415 V, 3 Ph., 4 wire, 50 Hz. A.C. system, instrumental panel, CTs, incoming and outgoing cable compartment. The Panel shall be complete with switches as per site requirement, interconnection, G.I. earth busbar of adequate size covering the total length of switch board with drilled holes, G.I. bolts, nuts, washers etc. as directed by E-I-C. The cubicle should be painted with two coats of light grey synthetic enamel paint over two coats of zinc chromate primer. The complete fabrication, construction shall be done as per the site condition and conforming to the relevant IS. Name plate of Panels Danger Board, incoming and outgoing feeders with Ampere rating of switches are to be fixed up on front door above or below the respective switches. Approval of Manufacturer's drawings from E-I-C.  The Panel consists of the following  NCOMING:  1 No.: 415V, 160A 4P MCCB (36 KA) for Mains, 1 No.: 415V, 125A 4P MCCB (36 KA) for DG, (Ics=Icu=100%)  1 No.: 415V, 160A 4P On-Load Changeover Switch 2 No.: Digital Multi Function Meter (MFM) for Current, Voltage, Frequency, Power.  6 Nos.: LED Phase indicating lamps, 6 Nos.: Suitable CTS(200/5)  PVC sleeved TPN Tinned Copper Busbar  35mm x 6mm for phases and neutral. (2sets)  G.I. EARTH BUSBAR25mm x 3mm covering the total length of panel.  OUTGOING:  Termination I: (To be connected with C.O.)  3 No 32A DP MCB for Glow Sign Board and others, 1 No 63A 4P MCCB(25KA) for Raw Power VTPN, 1 No 63A 4P MCCB for UPS, 1 No. 63A (36 KA) 4P MCCB for ATM  Termination-II: (Not to be connected with C.O.)  1 Nos. 100A 4P MCCB(25KA) for AC VTPN, 1 no 63A TPN spare	SET	1		
2.1	(A) UPS INCOMING DB: Supply of all required materials and fixing of input UPS box (Company made) having provision of the following arrangement complete with all respects per the direction of engineer in charge. Incoming: 1 No. 63A (10KA) TPN MCB Outgoing: 2 Nos. 63 A (10KA) DP MCB		1		
	(B) UPS OUTGOING DB: Supply of all required materials and fixing of output UPS box (Company made) having provision of the following arrangement complete with all respects per the direction of engineer in charge. <i>Incoming:</i> 1 no. 63 A DP MCB <i>Outgoing:</i> 3 No. 40A (10KA) DP MCB		1		
3	SITC of following VTPN Distribution Board (HVAC DB), having vertical fishbone busbar type, factory assembled wall mounted, sheet metal fabricated, fully powder coated, having dust proof & vermin proof hinged door with all internals such as DIN channels, neutral link, internal wiring complete with double earthing lugs including DB wiring dressing with ferruling, termination of circuits with ping type copper lugs, etc. housing following switchgears. (Schneider / ABB/Legrand / Siemens / L&T make)				
3.1	Incoming:1 no 415V ,4P,63A MCCB,25/36KA rating(L&T/ABB/SIEMENS) outgoing:- 8 nos 40A SP MCB(10KA), FOR RPDB/LDB/BM AC etc	SET	1		
3.2	Incoming:1 no 415V ,4P,100A MCCB,25/36KA rating(L&T/ABB/SIEMENS) outgoing:- 12 nos 40A SP MCB, FOR AC	SET	1		
4	RAW POWER DB/ LIGHT DB / COMPUTER DB Supply and installation of following <b>metallic double door</b> MCB Distribution Board with MCB having breaking capacity of 10 KA (minimum) complete with busbar, interconnection, painting, mounted on flat iron frame on wall/flushed with finished wall by chase cutting, mending good to original finish painting etc. as required. Name plate & number of DBs are to be fixed up on front door of DBs for their identification.				
а	CDB:Consumer unit SPN MCB DB complete with busbar and the following MCBs. INCOMING: 1 No. 240V 40A (10KA) DP RCBO OUTGOING:8 Nos. 240V 10A (10 KA ) SP MCB		2		

b	LDB: Consumer unit SPN MCB DB complete with busbar and the following MCBs. INCOMING: 1 No. 240V 40A (10KA) DP RCBO OUTGOING: 8 Nos. 240V 10A (10 KA) SP MCB	No.	2	
С	UPS DB for CCTV, fire alarmetc: Consumer unit SPN MCB DB complete with busbar and the following MCBs. INCOMING: 1 No. 240V 40A (10KA) DP RCBO OUTGOING: 4 Nos. 240V 10A (10 KA) SP MCB	No.	1	
d	RPDB :Consumer unit SPN MCB DB complete with busbar and the following MCBs. INCOMING: 1 No. 240V 40A (10KA) DP RCBO OUTGOING: 8 Nos. 240V 10A (10 KA) SP MCB	No.	2	
5	Wiring flame retardant FRLS/FRLSH as mentioned in rows below in MS conduit of IS specification of proper size with all material supply installation and commissioning complete from DB. The wiring shall be carried out on surface above false ceiling, and below of false ceiling by chiseling the existing surface and plastering the same with cement etc., or as cutting of tiles(with finishing), as per site conditions after fixing the MS conduit with all accessories like saddles screws, bends T-joint etc (POLYCAB/KEI/RR-KEBEL/FINOLEX/EQUIVALENT AS APPROVED BY E-I-C)			
а	With FRLS 2 nos. 6 Sq.mm + 1 no. 2.5 Sq.mm. (green colour for earth) PVC insulated copper wire in ms conduit for UPS Outgoing / LDB/RPDB/CDB	Mtr	175	
b	With FRLS 4 nos. 6 Sq.mm + 1 no. 2.5 Sq.mm. (green colour for earth) PVC insulated copper wire in ms conduit for UPS input	Mtr	35	
c 6	With FRLS 2 nos. 4 Sq.mm + 1 no. 2.5 Sq.mm. (green colour for earth) PVC insulated copper wire in ms conduit for AC (1.5 tr) as per direction of E-I-C.	Mtr	125	
	SUPPLY, LAYING, LUGGING, DRESSING, GLANDING, FINISHING, TESTING AND COMMISSIONING OF POWER CABLE: Following 1.1KV grade fire resistant <b>A2XFY</b> XLPE armored aluminium conductor cable with one no. <b>10 SWG GI wire</b> , laying of the cable partly on wall/column including supply and fixing with 300mm apart MS clamps/galvanized bar saddles and double compression type <b>brass</b> cable gland <b>Dowel make</b> along with rubber rings for dust and moisture proof entry of the cable and finishing the ends by crimping method <b>(POLYCAB/FINOLEX/NICCO/UNIVERSAL)</b>			
5.1	SITC of 3.5CX 70 SQMM cable incoming cable	Mtr	55	
5.2	SITC of 3.5CX 50 SQMM cable incoming cable for AC VTPN	Mtr	25	
5.3	SITC of 3.5CX 35 SQMM cable incoming cable for E-corner , Raw Power VTPN and UPS Input	Mtr	60	
7	(A) COMPUTER SOCKET OUTLET WITH WIRING Computer socket outlet cluster point including supply and fixing of modular type socket outlet clusters components and its wiring from CDB, complete in all respect as detailed below. Each computer socket outlet cluster comprising the following 5. Nos. 6/16A 5 pin modular type International sockets 1 No. 16A modular type common controlling switch with indicator on table top with 2 Nos. 2.5 Sq.mm. + 1 x 1.5 Sq.mm.FRLS (green colour for earth) PVC insulated copper wire in pre - laid (as per ISI) M.S. conduit including interconnection, painting etc. as required to be completed in all respect from CDB to Computer point.	No.	8	
	(B) COMPUTER SOCKET OUTLET AND ITS WIRING Computer socket outlet cluster point including supply and fixing of modular type socket outlet clusters components complete in all respect as detailed below. Each computer socket outlet cluster comprising the following 3 Nos. 6/16A 5 pin modular type International sockets 1 No. 16A modular type common controlling switch with indicator on table top with 2 Nos. 2.5 Sq.mm. + 1 x 1.5 Sq.mm. PVC insulated copper wire (1.1 KV grade FRLS/FR-LSH) in pre - laid (as per ISI) M.S. conduit including interconnection, painting etc. as required to be completed in all respect from CDB to Computer point. (proper colour code must be followed)	No.	3	

	Sneet			
	C ) UPS/ RAW POWER SOCKET OUTLET AND ITS WIRING Raw power socket outlet cluster point including supply and fixing of modular type socket outlet clusters components AND WIRING 1100V grade, FRLS complete in all respect as detailed below. Each computer socket outlet cluster comprising the following 2 Nos. 6A/16A 5 pin modular type International sockets, 1no 20A modular MCB with 1 No. 16/20A modular type controlling switch with 2 Nos. 2.5 Sq.mm. + 1 x 1.5 Sq.mm. (green colour for earth) PVC insulated copper wire in pre - laid (as per ISI) M.S. conduit including interconnection, painting etc. as required to be completed in all respect from RPDB to Raw Power Outlet. Proper colur code must be followed.	No.	9	
	D) UPS / RAW POWER SOCKET OUTLET AND ITS WIRING Raw power socket outlet cluster point including supply and fixing of modular type socket outlet clusters components AND WIRING 1100V grade, FRLS complete in all respect as detailed below. Each computer socket outlet cluster comprising the following 1 Nos. 6A/16A 5 pin modular type International sockets with indicator 1 No. 16/20A modular type controlling switch ANDmodular MCB(20A) with 2 Nos. 2.5 Sq.mm. + 1 x 1.5 Sq.mm. (green colour for earth) PVC insulated copper wire in pre - laid (as per ISI) M.S. conduit including interconnection, painting etc. as required to be completed in all respect from RPDB to Raw Power Outlet. Proper colur code must be followed.	No.	4	
8	SITC of metal clad socket MCB for AC point with controlling 32 A DP MCB with industrial top complete in all respects in suitable enclosure at proposed AC locations at 4.5 ft from the floor or as required.		7	
	. SITC of <b>OBO Betterman</b> make earthing system – * - UL Listed Earth Electrode - Copper bonded low carbon steel electrode, coating 250 microns - Tested as per IEC 62561-2 - Meets the requirement of IS 3043 and IEC 60364-5-54 - Tested for short circuit withstanding capacity - High tensile strength In one set it should include: a) One nos of Earthing rod-Type 17 3000 CCER, Length – 3000 mm Outer Dia – 17.2 mm Copper bonded low carbon steel Electrode WITH 250 microns copper bonded b) One bag (25 KG) Earth Enhancement Compound confirming to IEC 62561-7 c) One nos of universal clamp . The work shall also include required masonry work, Cl cover plate & Earthing name plate. The vendor shall also submit the earth test report with required values. Pics of earthing to be shown.		2	
10.1	SITC of Earth distribution Box (Bus Bar Station) to be installed in the branch near Main Panel and UPS, comprising of a bus bar of 3x25x180mm cu strip	SET	2	
	Supply and laying of 8 SWG Cu cotton coated wire in 20mm dia rigid PVC conduit for earthing From the existing earth pit to the Main panel/UPS	Mtr.	90	

	Silect			
''	POINT WIRING AND CIRCUIT WIRING Point wiring with FRLS 1100 V grade 3 nos. single core 1.5 sq.mm. and 1 for common earth by looping method) PVC insulated stranded copper conductor wire (IS:694) through suitable size M.S. conduit (ISI marked embossed on conduit surface) by thred cutting, complete with junction box, circular box, elbows, bends, couplers and other accessories on surface above false ceiling or concealed by chase cutting on wall from light & fan switch board to light, fan & 6A socket outlet on the same switch board or separately mounted switch board. The work includes supply and fixing of all materials such as modular type 6A switch for light and fan point, 6A 2/3 pin shuttered socket outlet with switch in each switch board, 3 plate ceiling rose / angle or batten holder etc. as required. The point wiring also includes circuit wiring with FRLS 1100 V grade 2 nos. single core 2.5 sq.mm. + 1 no. single core 1.5 sq.mm. PVC insulated stranded copper conductor cable (IS:694) through suitable size M.S. conduit as described above from DB to switch board, interconnection, mending good all damages to original finish, painting etc.			
а	1 Light control by 1 switch	No.	40	
b	2 /3 Light control by 1 switch	No.	25	
Ë	= 1.5 E.g. Control by Formon	<del></del> -	⊢∸	
С	UPS light point	No.	6	
d	Glow sign board wiring	No.	1	
е	Exhaust fan point	No.	6	
	Ceiling fan point with supply and fixing of Electronic Regulator as required as per site	_		
f	conditions.	No.	2	
g	1x16A 2/3 pin modular socket with switch on separate switch board outside the Cash Room complete with wiring. Suitable Top to be provided for supply to Cash Room. /RECORD ROOM/STATIONERY ROOM	No.	2	
h	Wall fan point with socket	No.	12	
i	3 pin 6/10A modular socket with switch in board	No.	8	
12	Supply and fixing of ding-dong calling bell with complete wiring in BM's Chamber as per direction of E-I-C	No.	1	
13	MAIN TPN SFU: Supply, installation, testing and commissioning (SITC) of following TPN SFU with HRC fuses in sheet steel enclosure with cable end-box on MS Angle Frame/ MS Legs/ wall with interconnection, painting and finishing.			
	160A TPN SFU with HRC fuses	No.	1	
	PART B-SUPPLY AND FITTING OF ELECTRICAL FITTINGS			
	SITC of 2'x2' LED white glow light & fixtures recessed type square LED downlight in white powder coated extruded alumunium diecast housing equipped with specially designed alumunium heat sink and energy efficient LED driver with all interconnections and fixing arrangement as required. Further light should be clamped with hook in ceiling. The work shall also include earthing connection with lugging to the body of fixture. MAKE :-(Philips/Havells/Opulus/crompton Equivalent as approved by E-I-C)(lumens>3000,<40watts,life>50000hrs)	No.	25	
15	Supply & Fixing of 15W LED Downlighter recessed mounted of make complete with all accessories	No.	8	
16	Supply & fixing of 20W/22W LED T5 Batten fitting complete with all respect.	No.	15	
17	Supply & fixing of 35W LED Street Light with suitable mounting pipe etc. Of complete in all respect	No.	4	
	Supply & fixing of 450mm sweep, oscillating type, wall mounting, multi speed wall fan metal blades three pin complete with all respect as per direction of Bank/E-I-C. Fan body to be earthed if 3-pin not available in the Market.		10	
19	SITC of 1200MM ceiling fan	No.	2	
		110.		-
20	SITC of 9" dia 230V,1400 rpm exhaust fan as in toilets, ups room, toilets etc.	No.	5	

	Sheet1			
	PART C- LAN CABLING WORK			
21	Supply of 1 mtr. Long E-CAT 6 PATCH CHORD (Make: D-LINK, AMP, HCL, Legrand)	No.	16	
22	Supply of 2 mtr. Long E-CAT 6 PATCH CHORD  (Make: D-LINK, AMP, HCL, Legrand)	No.	10	
23	INTERNET SOCKET WITH DATA CABLE:: SITC of modular RJ-45 internet sockets with suitable mounting box (modular type) including all inter-connections as required with front plate D link or equivalent make approved by the bank connections etc as required along with supply, laying, concealing of CAT 6 LAN cables upto 30 metres or less or as per site conditions in rigid pvc conduit pipes complete in all respects from Data Rack to I/O points. Rates to include cost of LAN cable and its installation.	No.	17	
24	Supply & installation of 9U Rack with power supply arrangement, ventilation fan, mounting racks ect. Complete with all accessories.	No.	1	
25	SITC of 24 port Patch Panel complete in all respects.	No.	1	
26	ONLOAD CHANGE OVER SWITCH: SITC of 1 no. 415V, 63A, 2P with on indication on load Change over switch with suitable enclosure. Complete with all respect.	No	1	
	Charges for making and submitting neat and clean computerised Electrical Drawing of the Branch indicating SLD of the Branch, indicating DB, switch boards, etc along with proper numbering and indicating power flow and laminating the same.	SET	1	
	Charges for making and submitting neat and clean computerised lan WIRING Drawing of the Branch indicating Data Rack , lan wiring to different I/O boxes etc along with proper numbering and laminating the same		1	
	Supply & Installation of single color (warm white / any other approved color) flexible LED strip light for cove including required rated driver / power supply in multiples of 1 Rmtr as approved along with all necessary hardware & accessories, etc. Complete as required (PHILIPS / WIPRO / CGL / GE /OPULUS/HAVELLS)	Rmt	65	
30	SITC of LED 5W/6w light & fixture recessed type ROUND DOWNLIGHTER in gypsum cove with all interconnection and fixing arrangements as Required.	No.	50	
	ELOBBY WORKS			
31	(a) TPN DB for ATM/Elobby: Consumer unit TPN MCB DB complete with busbar and the following MCBs. INCOMING: 1 No. 415V 63A 10KA FP MCB OUTGOING: 2 Nos. 240V 20A/25A 10 KA SP MCB for AC, 2 No 6A/10A MCB for Light points, 1Nos 32 A MCB spare, 1 nos 32 A MCB for UPS	No.	1	
32	SITC of metal clad socket MCB for AC point with controlling 20 A DP MCB with industrial top complete in all respects in suitable enclosure.	No.	2	
33	UPS/ RAW POWER SOCKET OUTLET AND ITS WIRING Raw power socket outlet cluster point including supply and fixing of modular type socket outlet clusters components AND WIRING 1100V grade, FRLS complete in all respect as detailed below. Each computer socket outlet cluster comprising the following 2 Nos. 6A/16A 5 pin modular type International sockets. 1 No. 16/20A modular type controlling switch with 2 Nos. 2.5 Sq.mm. + 1 x 1.5 Sq.mm. (green colour for earth) PVC insulated copper wire in pre - laid (as per ISI) M.S. conduit including interconnection, painting etc. as required to be completed in all respect from UPS/UPS DB. Proper colur code must be followed. (IO BOX AND COMPUTER SOCKET SOCKET SHOULD BE COVERED.)	No.	3	

_				 
34	Copper bonded Rod Earthing. SITC of OBO Betterman/JK/JEF eco safe/ make earthing system — * - UL Listed Earth Electrode - Copper bonded low carbon steel electrode, coating 250 microns - Tested as per IEC 62561-2 - Meets the requirement of IS 3043 and IEC 60364-5-54 - Tested for short circuit withstanding capacity - High tensile strength In one set it should include: a) One nos of Earthing rod-Type 17 3000 CCER, Length — 3000 mm Outer Dia — 17.2 mm Copper bonded low carbon steel Electrode WITH 250 microns copper bonded b) One bag (10 KG) Earth Enhancement Compound confirming to IEC 62561-7 c) One nos of universal clamp.	No.	1	
35	POINT WIRING  Point wiring with 1100 V grade 3 nos. single core 1.5 sq.mm. and 1 for common earth by looping method) PVC insulated stranded copper conductor wire (IS:694) through suitable size M.S. conduit (ISI marked embossed on conduit surface) by thred cutting, complete with junction box, circular box, elbows, bends, couplers and other accessories on surface above false ceiling or concealed by chase cutting on wall from light & fan switch board to light, fan & 6A socket outlet on the same switch board or separately mounted switch board. The work includes supply and fixing of all materials such as modular type 6A switch for light and fan point, 6A 2/3 pin shuttered socket outlet with switch in each switch board, 3 plate ceiling rose / angle or batten holder etc. as required. The point wiring also includes circuit wiring with 1100 V grade 2 nos. single core 2.5 sq.mm. + 1 no. single core 1.5 sq.mm. PVC insulated stranded copper conductor cable (IS:694) through suitable size M.S. conduit as described above from DB to switch board, interconnection, mending good all damages to original finish, painting etc.			
	1 Light control by 1 switch	No.	2	
	2 Light control by 1 switch	No.	2	
	Glow sign board wiring	No.	1	
	Wall fan point	No.	1	
	UPS light point	No.	1	
	PART B-SUPPLY AND FITTING OF ELECTRICAL FITTINGS			
36	Supply & Fixing of 36W-2'x2' LED Panel light recessed mounted of Syska / Phillips / Wipro /OPULUS/ CG make complete with all accessories.	No.	2	
37	SITC of LED 5W/6w light & fixture recessed type ROUND DOWNLIGHTER with all interconnection and fixing arrangements as Required.	No.	3	
38	SITC of warm white led tube light 18 watt	No.	3	
39	Supply & fixing of 450mm sweep, oscillating type, wall mounting, multi speed wall fan metal blades three pin complete with all respect as per direction of Bank/E-I-C.	No.	1	
40	Supply and fixing of 8 swg copper cotton coated wire in pvc pipe as laying required as per site requirement with all accessories	Mtr	40	
41	UPS DB: Supply of all required materials and fixing of output UPS box (Company made) having provision of the following arrangement complete with all respects per the direction of engineer in charge. <i>Incoming:</i> 1 no. 25 A DP MCB <i>Outgoing:</i> 2 No. 10A/16A (10KA) DP MCB		1	

					1
42	INTERNET SOCKET WITH DATA CABLE:: SITC of modular RJ-45 internet sockets with suitable mounting box (modular type) including all inter-connections as required with front plate D link or equivalent make approved by the bank connections etc as required along with supply , laying ,concealing of CAT 6 LAN cables upto 30 metres or less or as per site conditions in rigid pvc conduit pipes complete in all respects from Data Rack to I/O points. Rates to include cost of LAN cable and its installation.	No.	6		
43	SITC of Earth distribution Box (Bus Bar Station) to be installed in the branch near Main Panel and UPS, comprising of a bus bar of 3x25x180mm cu strip	SET	1		
44	Supply & Installation of 20A, timer switch with 2 no.s of 20A DP MCB's alongwith suitable size enclosure box for switching of A.C.'s, etc. alongwith 2NO 25A 1M contactor in the same enclosure box for controlling 2 no.s of AC power circuit through Timer for E lobby/ ATM A/C's through timer & contactor including all necessary hardware & accessories, etc. complete as required.	SET	1		
45	UPS INPUT:- Incoming 3 PIN ( 2P+1E) industrial type socket with matching plug and MCB:- 20/32Amp DP, UPS OUTPUT:- Incoming 3 PIN (2P+1E) industrial type socket with matching plug and MCB:20/32 Amp DP 1No. Make-(Legrand/L&T/Schneider)	SET	1		
46	SITC of 63A 2P Changeover switch in sheet steel enclosure with side handle complete in all respects as per direction of E-I-C.	No.	1		
47	SITC of 63A TPN SFU with HRC fuses in sheet steel enclosure complete in all respects as per direction of Bank/E-I-C.	No.	1		
48	With FRLS 2 nos. 4 Sq.mm + 1 no. 2.5 Sq.mm. (green colour for earth) PVC insulated copper wire in ms conduit as per direction of E-I-C.	Mtr	20		
	soppor time in the certain ac per ancealer of 2 T e.				
	Soppor mile in the certain as per ansealer of 2 i e.		TOTA	ıL (Rs.)	
	contingency (5%)		TOTA	L (Rs.)	
	contingency (5%)		TOTA	LL (Rs.)	
			TOTA	ıL (Rs.)	
NOTE:	contingency (5%)  Grand Total  The rate quoted shall be firm and shall include all costs, allowances, Charges, levies, Royalties, Cess, transportation etc. but excluding GST as applicable which will be reimbursed by the Bank as per Government norms prevailing from time to time. Contractor's are advised to visit the site before quoting. The quantities are tentative may increase or decrease as per site requirement.		TOTA	aL (Rs.)	
NOTE:	contingency (5%)  Grand Total  The rate quoted shall be firm and shall include all costs, allowances, Charges, levies, Royalties, Cess,transportation etc. but excluding GST as applicable which will be reimbursed by the Bank as per Government norms prevailing from time to time. Contractor's are advised to visit the site before quoting. The quantities are tentative may		TOTA	aL (Rs.)	
NOTE:	contingency (5%)  Grand Total  The rate quoted shall be firm and shall include all costs, allowances, Charges, levies, Royalties, Cess, transportation etc. but excluding GST as applicable which will be reimbursed by the Bank as per Government norms prevailing from time to time. Contractor's are advised to visit the site before quoting. The quantities are tentative may increase or decrease as per site requirement.  Recommended Manufacturers		TOTA	IL (Rs.)	
NOTE:	contingency (5%)  Grand Total  The rate quoted shall be firm and shall include all costs, allowances, Charges, levies, Royalties, Cess, transportation etc. but excluding GST as applicable which will be reimbursed by the Bank as per Government norms prevailing from time to time. Contractor's are advised to visit the site before quoting. The quantities are tentative may increase or decrease as per site requirement.  Recommended Manufacturers  Cables- (POLYCAB/FINOLEX/NICCO/UNIVERSAL)		TOTA	ıL (Rs.)	
NOTE:	contingency (5%)  Grand Total  The rate quoted shall be firm and shall include all costs, allowances, Charges, levies, Royalties, Cess, transportation etc. but excluding GST as applicable which will be reimbursed by the Bank as per Government norms prevailing from time to time. Contractor's are advised to visit the site before quoting. The quantities are tentative may increase or decrease as per site requirement.  Recommended Manufacturers  Cables- (POLYCAB/FINOLEX/NICCO/UNIVERSAL)  WIRES -  (POLYCAB/KEI/FINOLEX/RR-KABEL		TOTA	aL (Rs.)	
NOTE:	contingency (5%)  Grand Total  The rate quoted shall be firm and shall include all costs, allowances, Charges, levies, Royalties, Cess, transportation etc. but excluding GST as applicable which will be reimbursed by the Bank as per Government norms prevailing from time to time. Contractor's are advised to visit the site before quoting. The quantities are tentative may increase or decrease as per site requirement.  Recommended Manufacturers Cables- (POLYCAB/FINOLEX/NICCO/UNIVERSAL)  WIRES -  (POLYCAB/KEI/FINOLEX/RR-KABEL PROTECTIVE DEVICE	/ALEN			3Y E-I-C
NOTE:	contingency (5%)  Grand Total  The rate quoted shall be firm and shall include all costs, allowances, Charges, levies, Royalties, Cess, transportation etc. but excluding GST as applicable which will be reimbursed by the Bank as per Government norms prevailing from time to time. Contractor's are advised to visit the site before quoting. The quantities are tentative may increase or decrease as per site requirement.  Recommended Manufacturers Cables- (POLYCAB/FINOLEX/NICCO/UNIVERSAL)  WIRES -  (POLYCAB/KEI/FINOLEX/RR-KABEL  PROTECTIVE DEVICE  DB/MCCB/MCB/RCBO/ELCB- LEGRAND/L&T/SIEMENS/ABB(T MAX)/EQUIVCHANGE-OVER-SWITCH - L&T/HPL /SOCOMEC/ABB	/ALEN			BY E-I-C
NOTE:	contingency (5%)  Grand Total  The rate quoted shall be firm and shall include all costs, allowances, Charges, levies, Royalties, Cess, transportation etc. but excluding GST as applicable which will be reimbursed by the Bank as per Government norms prevailing from time to time. Contractor's are advised to visit the site before quoting. The quantities are tentative may increase or decrease as per site requirement.  Recommended Manufacturers Cables- (POLYCAB/FINOLEX/NICCO/UNIVERSAL)  WIRES -  (POLYCAB/KEI/FINOLEX/RR-KABEL  PROTECTIVE DEVICE  DB/MCCB/MCB/RCBO/ELCB- LEGRAND/L&T/SIEMENS/ABB(T MAX)/EQUIV. CHANGE-OVER-SWITCH - L&T/HPL /SOCOMEC/ABB  SWITCHES/SOCKETS/REGULATOR		IT AS A	APPROVED E	BY E-I-C
NOTE:	contingency (5%)  Grand Total  The rate quoted shall be firm and shall include all costs, allowances, Charges, levies, Royalties, Cess, transportation etc. but excluding GST as applicable which will be reimbursed by the Bank as per Government norms prevailing from time to time. Contractor's are advised to visit the site before quoting. The quantities are tentative may increase or decrease as per site requirement.  Recommended Manufacturers Cables- (POLYCAB/FINOLEX/NICCO/UNIVERSAL)  WIRES -  (POLYCAB/KEI/FINOLEX/RR-KABEL  PROTECTIVE DEVICE  DB/MCCB/MCB/RCBO/ELCB- LEGRAND/L&T/SIEMENS/ABB(T MAX)/EQUIV CHANGE-OVER-SWITCH - L&T/HPL /SOCOMEC/ABB  SWITCHES/SOCKETS/REGULATOR  LEGRAND/ROMA/MK(BLENZ)/NORTH WEST/L&T/SCHNEIDER/CRABATREE		IT AS A	APPROVED E	BY E-I-C
NOTE:	contingency (5%)  Grand Total  The rate quoted shall be firm and shall include all costs, allowances, Charges, levies, Royalties, Cess, transportation etc. but excluding GST as applicable which will be reimbursed by the Bank as per Government norms prevailing from time to time. Contractor's are advised to visit the site before quoting. The quantities are tentative may increase or decrease as per site requirement.  Recommended Manufacturers Cables- (POLYCAB/FINOLEX/NICCO/UNIVERSAL)  WIRES -  (POLYCAB/KEI/FINOLEX/RR-KABEL  PROTECTIVE DEVICE  DB/MCCB/MCB/RCBO/ELCB- LEGRAND/L&T/SIEMENS/ABB(T MAX)/EQUIV. CHANGE-OVER-SWITCH - L&T/HPL /SOCOMEC/ABB  SWITCHES/SOCKETS/REGULATOR		IT AS A	APPROVED E	BY E-I-C
NOTE:	contingency (5%)  Grand Total  The rate quoted shall be firm and shall include all costs, allowances, Charges, levies, Royalties, Cess, transportation etc. but excluding GST as applicable which will be reimbursed by the Bank as per Government norms prevailing from time to time. Contractor's are advised to visit the site before quoting. The quantities are tentative may increase or decrease as per site requirement.  Recommended Manufacturers  Cables- (POLYCAB/FINOLEX/NICCO/UNIVERSAL)  WIRES -  (POLYCAB/KEI/FINOLEX/RR-KABEL  PROTECTIVE DEVICE  DB/MCCB/MCB/RCBO/ELCB- LEGRAND/L&T/SIEMENS/ABB(T MAX)/EQUIV.  CHANGE-OVER-SWITCH - L&T/HPL /SOCOMEC/ABB  SWITCHES/SOCKETS/REGULATOR  LEGRAND/ROMA/MK(BLENZ)/NORTH WEST/L&T/SCHNEIDER/CRABATREE  METAL CLAD SOCKET & PLUG- L&T/LEGRAND/ABB/C&S  MEASURING INSTRUMENTS-  AE/ IMP/ L&T/ GE/ TELEMECANIQUE/ PROK/EQUIVALENT		IT AS A	APPROVED E	BY E-I-C
NOTE:	Contingency (5%)  Grand Total  The rate quoted shall be firm and shall include all costs, allowances, Charges, levies, Royalties, Cess, transportation etc. but excluding GST as applicable which will be reimbursed by the Bank as per Government norms prevailing from time to time. Contractor's are advised to visit the site before quoting. The quantities are tentative may increase or decrease as per site requirement.  Recommended Manufacturers  Cables- (POLYCAB/FINOLEX/NICCO/UNIVERSAL)  WIRES -  (POLYCAB/KEI/FINOLEX/RR-KABEL  PROTECTIVE DEVICE  DB/MCCB/MCB/RCBO/ELCB- LEGRAND/L&T/SIEMENS/ABB(T MAX)/EQUIV.  CHANGE-OVER-SWITCH - L&T/HPL /SOCOMEC/ABB  SWITCHES/SOCKETS/REGULATOR  LEGRAND/ROMA/MK(BLENZ)/NORTH WEST/L&T/SCHNEIDER/CRABATREE  METAL CLAD SOCKET & PLUG- L&T/LEGRAND/ABB/C&S  MEASURING INSTRUMENTS-  AE/ IMP/ L&T/ GE/ TELEMECANIQUE/ PROK/EQUIVALENT  LED LIGHTS -	/ABB/	IT AS A	APPROVED E	BY E-I-C
NOTE:	Contingency (5%)  Grand Total  The rate quoted shall be firm and shall include all costs, allowances, Charges, levies, Royalties, Cess, transportation etc. but excluding GST as applicable which will be reimbursed by the Bank as per Government norms prevailing from time to time. Contractor's are advised to visit the site before quoting. The quantities are tentative may increase or decrease as per site requirement.  Recommended Manufacturers  Cables- (POLYCAB/FINOLEX/NICCO/UNIVERSAL)  WIRES -  (POLYCAB/KEI/FINOLEX/RR-KABEL  PROTECTIVE DEVICE  DB/MCCB/MCB/RCBO/ELCB- LEGRAND/L&T/SIEMENS/ABB(T MAX)/EQUIV.  CHANGE-OVER-SWITCH - L&T/HPL /SOCOMEC/ABB  SWITCHES/SOCKETS/REGULATOR  LEGRAND/ROMA/MK(BLENZ)/NORTH WEST/L&T/SCHNEIDER/CRABATREE  METAL CLAD SOCKET & PLUG- L&T/LEGRAND/ABB/C&S  MEASURING INSTRUMENTS-  AE/ IMP/ L&T/ GE/ TELEMECANIQUE/ PROK/EQUIVALENT  LED LIGHTS -  PHILIPS/ GE/OPULUS/HAVELLS/CROMPTON/EQUIVALENT AS APPROVED	/ABB/	IT AS A	APPROVED E	BY E-I-C
NOTE:	Contingency (5%)  Grand Total  The rate quoted shall be firm and shall include all costs, allowances, Charges, levies, Royalties, Cess, transportation etc. but excluding GST as applicable which will be reimbursed by the Bank as per Government norms prevailing from time to time. Contractor's are advised to visit the site before quoting. The quantities are tentative may increase or decrease as per site requirement.  Recommended Manufacturers  Cables- (POLYCAB/FINOLEX/NICCO/UNIVERSAL)  WIRES -  (POLYCAB/KEI/FINOLEX/RR-KABEL  PROTECTIVE DEVICE  DB/MCCB/MCB/RCBO/ELCB- LEGRAND/L&T/SIEMENS/ABB(T MAX)/EQUIV.  CHANGE-OVER-SWITCH - L&T/HPL /SOCOMEC/ABB  SWITCHES/SOCKETS/REGULATOR  LEGRAND/ROMA/MK(BLENZ)/NORTH WEST/L&T/SCHNEIDER/CRABATREE  METAL CLAD SOCKET & PLUG- L&T/LEGRAND/ABB/C&S  MEASURING INSTRUMENTS-  AE/ IMP/ L&T/ GE/ TELEMECANIQUE/ PROK/EQUIVALENT  LED LIGHTS -	/ABB/	IT AS A	APPROVED E	BY E-I-C
NOTE:	Contingency (5%)  Grand Total  The rate quoted shall be firm and shall include all costs, allowances, Charges, levies, Royalties, Cess, transportation etc. but excluding GST as applicable which will be reimbursed by the Bank as per Government norms prevailing from time to time. Contractor's are advised to visit the site before quoting. The quantities are tentative may increase or decrease as per site requirement.  Recommended Manufacturers  Cables- (POLYCAB/FINOLEX/NICCO/UNIVERSAL)  WIRES -  (POLYCAB/KEI/FINOLEX/RR-KABEL  PROTECTIVE DEVICE  DB/MCCB/MCB/RCBO/ELCB- LEGRAND/L&T/SIEMENS/ABB(T MAX)/EQUIV. CHANGE-OVER-SWITCH - L&T/HPL /SOCOMEC/ABB  SWITCHES/SOCKETS/REGULATOR  LEGRAND/ROMA/MK(BLENZ)/NORTH WEST/L&T/SCHNEIDER/CRABATREE METAL CLAD SOCKET & PLUG- L&T/LEGRAND/ABB/C&S  MEASURING INSTRUMENTS-  AE/ IMP/ L&T/ GE/ TELEMECANIQUE/ PROK/EQUIVALENT  LED LIGHTS -  PHILIPS/ GE/OPULUS/HAVELLS/CROMPTON/EQUIVALENT AS APPROVED CEILING FAN/WALL FAN  CROMPTON/HAVELLS/ALMONARD/GOLD MEDAL  EXHAUST FAN - CROMPTON/ BAJAJ/ALSTOM/ALMONARD/GOLD MEDAL/H	/ABB/	GOLD	APPROVED E	BY E-I-C
NOTE:	contingency (5%)  Grand Total  The rate quoted shall be firm and shall include all costs, allowances, Charges, levies, Royalties, Cess, transportation etc. but excluding GST as applicable which will be reimbursed by the Bank as per Government norms prevailing from time to time. Contractor's are advised to visit the site before quoting. The quantities are tentative may increase or decrease as per site requirement.  Recommended Manufacturers  Cables- (POLYCAB/FINOLEX/NICCO/UNIVERSAL)  WIRES -  (POLYCAB/KEI/FINOLEX/RR-KABEL  PROTECTIVE DEVICE  DB/MCCB/MCB/RCBO/ELCB- LEGRAND/L&T/SIEMENS/ABB(T MAX)/EQUIV.  CHANGE-OVER-SWITCH - L&T/IPL /SOCOMEC/ABB  SWITCHES/SOCKETS/REGULATOR  LEGRAND/ROMA/MK(BLENZ)/NORTH WEST/L&T/SCHNEIDER/CRABATREE  METAL CLAD SOCKET & PLUG- L&T/LEGRAND/ABB/C&S  MEASURING INSTRUMENTS-  AE/ IMP/ L&T/ GE/ TELEMECANIQUE/ PROK/EQUIVALENT  LED LIGHTS -  PHILIPS/ GE/OPULUS/HAVELLS/CROMPTON/EQUIVALENT AS APPROVED  CEILING FAN/WALL FAN  CROMPTON/HAVELLS/ALMONARD/GOLD MEDAL  EXHAUST FAN - CROMPTON/ BAJAJ/ALSTOM/ALMONARD/GOLD MEDAL/H  Conduit	/ABB/	GOLD	APPROVED E	BY E-I-C
NOTE:	Contingency (5%)  Grand Total  The rate quoted shall be firm and shall include all costs, allowances, Charges, levies, Royalties, Cess, transportation etc. but excluding GST as applicable which will be reimbursed by the Bank as per Government norms prevailing from time to time. Contractor's are advised to visit the site before quoting. The quantities are tentative may increase or decrease as per site requirement.  Recommended Manufacturers  Cables- (POLYCAB/FINOLEX/NICCO/UNIVERSAL)  WIRES -  (POLYCAB/KEI/FINOLEX/RR-KABEL  PROTECTIVE DEVICE  DB/MCCB/MCB/RCBO/ELCB- LEGRAND/L&T/SIEMENS/ABB(T MAX)/EQUIV. CHANGE-OVER-SWITCH - L&T/HPL /SOCOMEC/ABB  SWITCHES/SOCKETS/REGULATOR  LEGRAND/ROMA/MK(BLENZ)/NORTH WEST/L&T/SCHNEIDER/CRABATREE METAL CLAD SOCKET & PLUG- L&T/LEGRAND/ABB/C&S  MEASURING INSTRUMENTS-  AE/ IMP/ L&T/ GE/ TELEMECANIQUE/ PROK/EQUIVALENT  LED LIGHTS -  PHILIPS/ GE/OPULUS/HAVELLS/CROMPTON/EQUIVALENT AS APPROVED CEILING FAN/WALL FAN  CROMPTON/HAVELLS/ALMONARD/GOLD MEDAL  EXHAUST FAN - CROMPTON/ BAJAJ/ALSTOM/ALMONARD/GOLD MEDAL/H	/ABB/	GOLD	APPROVED E	BY E-I-C