## SBI, YERRAGUNTLA BRANCH NEW PREMISES Estimate for Electrical Installation Works

	Estimate for Electrical Installation Works				
SI.N o.	Description	иом	Qty.	Rate (Rs.)	Amount (Rs.)
1	Main Panel: Supplying, Installing, testing and commissioning of fabricated floor cubicle type distribution Panel Board suitable for 415 V comprising of 3 Nos. 50 mm X 6 mm for phase and 40 mm X 6 mm for neutral copper bus bars with the following: 1 no. 200 A 4P MCCB of 25kA breaking capacity at incoming 1 no. 80 A 4P MCCB (for ESDB), 1 NO. 100 A 4P MCCBs (for AC DBs), 1 no. 63 A 4P MCCB (for spare), 3 no. 32 A SPMCB (for out door lighting & glow sign board, spare) at outgoing in compartmentalized chamber fully isolated with 2 mm thick steel sheet and 3 mm steel channel painted with 2 coats of red oxide primer paint followed by finishing paint with interconnection etc. as required. The MCCB should have adjustable overload setting With load/line interchangeability with thermo magnetic /static release.	No.s	1		
2	The price is to be inclusive of phase indicator lamps, multi-functional meter etc. Supply, installation, testing & commissioning of static type 2 kVAR 3 phase capacitor (to be connected in AC DB only)	No.s	1		
3	Supply ,installation ,testing and commissioning of Essential services DB:- VTPN DB – IP 43-IK 09 - approved make (MCB incomer) comprising of 80 A 4P MCB at incoming and 1 No. 63 A TPMCB (for light & raw power db at ground floor), 1 no. 40 A TPMCB (for ATM), 2 no. 40A SPMCB (for 2 no. 5kVA UPS), 1 nos of 40A SP MCB (for CM room AC) at outgoing with inter connection in PVC insulated color coded wire in PVC conduit cable socket including loop earth connection to earth bus bars etc. all complete including mending good the damage and painting.	No.s	1		
4	Supply ,installation ,testing and commissioning of <u>AC DB:</u> VTPN DB – IP 43-IK 09 - approved make(MCB incomer) comprising of 100 A 4P MCB of at incoming and 5 no. 32 A TPMCBs (for 3 TR cassette units) 3 no. 25 A SPMCBs (for individual HWM units) with inter connection in PVC insulated color coded wire in PVC conduit cable socket including loop earth connection to earth bus bars etc. all complete including mending good the damage and painting.		1		
	Supply, installation, testing and commissioning of TPN double door DB with 63 A 4PMCB as incomer and 12 no. 16 A SPMCBs & 6 no. 25 A SPMCBs at outgoing LIGHT & RAW POWER DB	No.s	1		
6	supply, installation, testing and commissioning of 100 A 4P on-load changeover with suitable enclosure with complete connections.	No.s	1		
7	Supply, installation, testing and commissioning of <u>UPS</u> incoming & outgoing DB: DP MCB box with 40 A DPMCB	No.s	4		
8	UPS Computer DB, SPN double door with 40A DP MCB as incomer & 8nos 16A SP MCB as outgoing.	No.s	2		
9	Supply, installation, testing and commissioning of DB with 32A 4P MCB for Cassette unit control	No.s	5		
10	Supply, installation, testing and commissioning of DB with 25A DPMCB for HWM units control	No.s	3		
11	supply, installation, testing and commissioning of SPN DB with 40 A TPMCB as incomer, 3 no. 25 A SPMCBs (for UPS), 1 no. 16 A SPMCB (for lighting circuit), 2 no. 25 a SPMCBs (for AC point) at out going <b>ATM DB</b>	No.s	1		
12	Supply, installation, testing and commissioning of DB with 100 A 4P MCB for master control of Acs at entrance gate	no.s	1		
13	Supply, installation, testing and commissioning of DB with 63 A 4P MCB for master control of lights at entrance gate	No.s	1		
14	AC point wiring: Wiring in PVC conduit of IS specification of Proper size with core PVC insulated stranded copper wire 1.1 KV grade and with all materials supply ,installation connection complete as per circuit diagram and as required with 3 no. 4 sq. mm (Phase, Neutral and Earth)	RM	45		

	Sub-main line Wiring:				
	Wiring in PVC conduit of IS specification of Proper size with core PVC insulated stranded				
15	copper wire 1.1 KV grade and with all materials supply ,installation connection complete as				
	per circuit diagram and as required from main DB to various Dbs: With 3nos 6sg.mm (Phase, Neutral and Earth	RM	75		
	With Shos osq. Init (Phase, Neutral and Lattin Wiring:	INIVI	75		
16	Wiring in PVC conduit of IS specification of Proper size with core PVC insulated stranded				
	copper wire 1.1 KV grade and with all materials supply ,installation connection complete as				
	per circuit diagram and as required from main DB to various Dbs:				
	With 5nos 6sq.mm (R,Y,B, Neutral and Earth)	RM	75		
	Wiring:		-		
	Wiring in PVC conduit of IS specification of Proper size with core PVC insulated stranded				
	copper wire 1.1 KV grade and with all materials supply ,installation connection complete as				
	per circuit diagram and as required from main DB to various Dbs:				
	With 5nos 4sq.mm (R,Y,B, Neutral and Earth)	RM	150		
	Wiring:				
	Wiring in PVC conduit of IS specification of Proper size with core PVC insulated stranded				
18	copper wire 1.1 KV grade and with all materials supply ,installation connection complete as				
	per circuit diagram and as required from main DB to various Dbs:		20		
	With 5nos 10sq.mm (R,Y,B, Neutral and Earth)	RM	30		
	<b>Cabling:</b> Supply and laying of following sizes of PVC/XLPE insulated and PVC sheathed 1.1 kV				
	grade aluminum conductor LT armoured UG cable laid in ground/partially in air including				
	excavation of cable trench upto depth of 75 cm. Refilling, protective brick covering, sand				
19	cushioning etc. complete handling of surplus soil, debris etc. to proper place as well as fixing to the walls with saddles, cable glands for connecting to the panels and appropriate end				
1	termination with copper lugs and providing of 2 nos. of 8 SWG GI wires as specified and				
	directed by the department				
	3.5 Core X 25 sq. mm	RM	35		
	Cabling:Supply and laying of following sizes of PVC/XLPE insulated and PVC sheathed 1.1 kV				
	grade aluminum conductor LT armoured UG cable laid in ground/partially in air including				
	excavation of cable trench upto depth of 75 cm. Refilling, protective brick covering, sand				
20	cushioning etc. complete handling of surplus soil, debris etc. to proper place as well as fixing				
20	to the walls with saddles, cable glands for connecting to the panels and appropriate end				
	termination with copper lugs and providing of 2 nos. of 8 SWG GI wires as specified and				
	directed by the department		150		
	4.0 core X 16 sq. mm <u>Computer point wiring</u> in PVC conduit of IS specification of proper size with 3nos 2.5sq.mm	RM	150		
	single core PVC insulated stranded copper wire 1.1KV grade and with all material supply				
1	installation and commissioning complete from CDB/PDB(Raw). The wiring shall be carried out				
1	on surface above false ceiling and concealed in the wall by chiseling the existing surface and				
	plastering the same with cement etc. after fixing the pvc conduit with all accessories like				
21	saddles screws, bends T-joint etc. 2 coats of painting Matching to the surface including supply				
1	installing, testing, commissioning of modular plate type switch and socket for computer				
	terminal on sheet steel enclosure (cadmium plated),duly fitted with screw to the steel				
	conduit and fixed to the wall partition furniture with all interconnection and proper earthing				
	All the opening shall be covered with blank plate and be sealed to make the box vermin.				
	proof.				
	UPS point: 4 no. 6A sockets fixed below the table, to be controlled by one no. 20 A modular				
а	DP switch above the table / counter. The boxes are to be fixed on the partitions by suitably		10		
<u>ہ</u>	chiseling / cutting, making good the damage.	Set	10		
a	UPS point: 3 no. 6A sockets fixed below the table, to be controlled by one no. 16 A modular DP switch above the table / counter. The boxes are to be fixed on the partitions by suitably				
	chiseling / cutting, making good the damage.	Set	8		
с	Raw power point: 2 no. 6A sockets fixed below the table to be controlled by one no. 16 A		2		
	modular switch above the table / counter. The boxes are to be fixed on the partitions by				
	suitably chiseling / cutting, making good the damage.	Set	15		

d	Raw power point: 1 no. 16 A controlled by 16 A switch. The boxes are to be fixed on the				
	partitions by suitably chiseling / cutting, making good the damage.	Set	12		
	General Wiring for light/fan/exhaust fan points using 3 X 1.5 1.1 kV grade PVC insulated				
	stranded copper conductor wire for phase, neutral and earth in 25 mm dia heavy duty PVC				
	conduit along with associated accessories like MS junction boxes, bends, saddles, screws etc.				
	concealed in wall, floor, under flooring, below false ceiling or on surface as well as suspended				
	from ceiling with 25mm X 3 mm MS flat suspenders duly painted above false ceiling from				
	individual light/Fan/Exhaust Fan point outlet. etc. to individual modular type switch boards, 6				
	Amp modular plate type switches etc., as required complete including circuit wiring with 3 X				
	2.5 sqmm. 1.1 kV grade PVC insulated stranded copper conductor wire and mending good to				
	damage and as per site requirement and as instructed by engineer. All the opening shall be				
	covered with blank plate and be sealed to make the box vermin proof.				
а	2 no. of lights controlled by one switch	Set	22.00		
	Wiring for 1 no. of lights by one switch.	Set	45.00		
	Wiring for Wall bracket fans / exhaust fan controlled by 6A switch at switch board			T	
	and 1 no. 6 A socket in MS box at ceiling level.	Set	16.00		
d	Wiring for Ceiling fans with electronic regulators	Set	8.00		
	Wiring for 6 A light plug controlled by 6 A switch on the same switch board along				
5	with switch and socket	Set	12		
f	Wirin for Call bell point for Branch Manager chamber along with the supply of call bell	Set	1.00		
	Wiring and installation of 6A light plug socket with 6A switch wiring including all accessories,				
-	as per the branch requirement in the banking hall	Set	10		
	Wiring for glow sign board and out side security lightingwith 3 X 4 sq.mm 1.1 kV grade PVC				
	insulated stranded copper conductor wire for phase, neutral and earth in 25 mm dia heavy				
	duty PVC conduit along with associated accessories like PVC junction boxes, bends, saddles,				
	screws etc.	Set	2		
24	Supply, installation, testing and commissioning of 1.1 kV grade 2.5 sq. mm flexible copper				
	cable 3 meter length connected at one end with 15 A three pin socket and other end				
	connected permanently to the switch board of safe room / locker room	Set	4		
25	Earth Stations: Supply, installing and commissioning of earth station including digging and				
	refilling back the pit with black soil and with 3mm x 600mm X 600 mm size copper plate duly				
	tinned through out the surface of the plate, placed at least 1.5Mtr, below the ground level				
	with 25 X 3 flat Cu strip fixed to the plate and providing 40mm,2mtr,long GI pipe with				
	reducer and funnel at top for watering pipe. As per IS 3043-1987 or latest version. The price				
	should be inclusive of preparation of brick masanary chamber, with covering place etc.	_	-		
26		Set	1		
	supplying and laying earth continuity wire of 8 SWG Cu insulated wire in 20 mm dia PVC	RM	10		
	conduit on the wall from earth plate to starting point of the line earth connector.	r (VI	10		
	Providing standard GI pipe earth station, with 100 mm dia 2500 mm long G I Pipe including excavation, construction of brick masonry chamber providing meshed funnel, electrode,				
	watering pipe, charcoal and salt fill, CI cover completely as per IS 3043-1987 or latest				
	revision. The rates to be inclusive of supply and laying of 8 SWG GI wire in 20 mm dia pvc conduit from earth pit to DB	Set	1		
28	Supply, installation, testing and commissioning of Recess mounted lumanaire of 2' X 2' flat	JCL	1		
	type modular 36W LED light fixture complete with electronic driver, wiring, heat sink, opal				
	acrylic diffuser etc. suitable for gyp board or metric false ceiling. The fixture shall be provided				
	with atleast three nos. 20mm dia knock out holes on the top side for fixing down rods and				
	wiring purpose.	Nos.	20		
	Supply, installation, testing and commissioning of Recessed decorative LED down lighter of				
	15W complete with electronic driver, wiring, heat sink, opal acrylic diffuser etc. suitable for				
	gyp board or metric false ceiling	No.s	43		
	Supply, installation, testing and commissioning of 15 / 18 W LED batten suitable for indoor				_
	application.	No.s	25		

31	Supply, installation, testing and commissioning of Supply, Installation, testing and			
	commissioning of holder type 7 W LED lamps complete including connections as required.			
	(Make Philips / Bajaj)	No.s	4	
32	Supply, installation, testing and commissioning of Exhaust fan 300 mm Crompton / Bajaj			
	/Usha / Havell's make (metal only)	No.s	5	
33	Supply, installation, testing and commissioning of Ceiling fan 1200 mm, Crompton / Bajaj			
	/Usha/ Havell's make	No.s	5	
34	Supply, installation, testing and commissioning of Wall bracket fan 450 mm			
	Crompton/Bajaj/Usha/Havell's make (whole body and blades should be of metal only)	No.s	12	
36	Supply, installation, testing and commissioning of LED indicator lamps (R, Y, B) with 3 no.s			
	lamp holders and 3 nos. 5 A swtches on a suitable board and wiring with 1.1 kV grade 3 X 1.5			
	sq.mm copper flexible wire in PVC pipe tapping power from EB cut outs.	Set	1	
37	supply and laying of 6mm thick rubber mat with ISI mark as required for UPS / Electrical room			
		No.s	1	

+ GST as applicable