PRIC	CE BID FOR ELECTRICAL WORK OF SBI SIDHPUR	BRA	NCH	AT SIL	HPUR.			
Sr. No.	DESCRIPTION	QTY	UNIT	RATE	AMOUN			
NOTE: ALL CHARIS OR CHASES IN WALLS / COLUMNS / SLABS MADE BY THE ELECTRICAL CONTRACTOR FOR INSTALLATION OF CONDUITS / S.B. / BOXES ETC. THE FILLING OF THE SAME IS IN THE SCOPE OF THE ELECTRICAL CONTRACTOR INCLUDING ALL NECESSITY MATERIAL AND LABOUR.								
	PART - A :::: BRANCH							
A	INTERNAL WIRING: Phase wire must be Red colour for LDB, Yellow colour for PDB & Blue for ACDB, Neutral Wire of Black colour & Green Wire for Earthing. Color code must be maintained. Tagging from DB MCB and Switch board must be done.							
1	SITC of point wiring in concealed in walls, furniture's & for above false ceiling, or on ceiling, on beams shall be fixed with saddles & spacers etc., with conduits taken in slab with 20 mm dia PVC Rigid conduits 1.5 mm thick ISI mark with 2 nos. of 1.5 sq. mm. phase & nutral & 1 nos. of 1.0 sq. mm. earthing with modular switch with company made flush metal box/surface PVC box etc. comp. with nec. main lines for switch board from LDB of mains of 2 nos. of 2.5 sq.mm wire and 1 no. of 1.0 sqmm pvc Insulated copper conductor wire FRLS type laying in with 20 mm/25 mm dia PVC rigid conduits 1.5 mm thick ISI mark .These will be used with point wiring of light, fan, ex. fan, callbell points, etc { Max. 3 Switchboards in one circuit - One Sp MCB }.Phase wire must be Red colour, Nutral Wire must be Black color & Green Wire for Earthing. Color code must be maintained. Tagging from Lighting DB MCB and Switch board must be done.							
1.1	One 5A switch controling one light / fan point.	33	nos					
1.2	One switch controlling Two light points .	24	nos					
1.3	5A socket outlet with 5A switch (on common board) (1 FOR WATER COOLER).	18	nos					
1.4	5A socket outlet with 5A SP switch (as an independent point) [for ex. Fan, wall fan , QMS, Token M/C Display, etc. points.]	18	nos					
1.5	Call bell point with bell push complete.	1	nos					
1.0	Can ben point with ben push complete.	1	1103					
1.6	SITC of loop light points of 2 nos. of 1.5 sq. mm. off wires & 1 nos. of 1.0 sq. mm. earth wire from Main panel timer of mains of 2 nos. of 2.5 sq.mm wire and 1 no.of 1.0 sqmm pvc Insulated copper conductor earth wire laying in with 20 mm/25 mm dia type PVC rigid conduits 1.5 mm thick ISI mark (This point is for Signage and Down Lighter Points at Entrance) - 3 for branch & 2 for E Lobby.	4	nos					

Page 1 of 12

PRICE BID FOR ELECTRICAL WORK OF SBI SIDHPUR BRANCH AT SIDHPUR					
Sr. No.	DESCRIPTION	QTY	UNIT	RATE	AMOUNT
1.7	SITC of 6/16 Amp. Switch and socket complete with necessory require wiring from LDB of 2 no of 2.5 sq mm wires and 1 no of 1.0 sq mm PVC Insulated copper conductor earth wire laying in with 20 mm/25 mm dia PVC rigid conduits 1.5 mm thick ISI mark. These will be used with point wiring of power points ,etc. No Looping of Neutral or earthing is allowed. Each point needs to provide seperate circuit. This Points Need to Be Connected through LDB. (For Cash Room, Locker Room, Record Room - wiring points).	3	nos		
1.8	SITC of 6/16 Amp. Switch and socket complete with necessory require wiring from PDB of 2 no of 4.0 sq mm wires and 1 no of 2.5 sq mm PVC Insulated copper conductor earth wire laying in with 20 mm/25 mm dia PVC rigid conduits 1.5 mm thick ISI mark. These will be used with point wiring of power points ,etc No Looping of Neutral or earthing is allowed. Each point needs to provide seperate circuit. This Points Need to Be Connected through PDB. (For Printer, Water Cooler, Freeze, Motor, Note Counting Machine points).	3	nos		
2	SITC of 20 A/ 25 A, 230 V, with DP ELCB, 100 mA all enclosed in a prefabricated M S boxes complete to the satisfaction of E.I.C. For SPLIT AC 1.5TR / 2.0 TR unit with necessory require wiring from ACDB of 2 no of 4.0 sqmm wires and 1 no of 2.5 sqmm PVC Insulated copper conductor wire FRLS type laying in with 20 mm/25 mm dia PVC rigid conduits 1.5 mm thick ISI mark. These will be used with point wiring of A.C. points ,etc . Color code must be maintained. Tagging from DP MCB and AC point must be done. This point should be installed near Split / window AC in concealed manner. No Looping of Neutral or earthing is allowed. Each point needs to provide seperate circuit. For Cassate AC power supply indoor or outdoor need to be given as per AC vendor's requirement. The height of switchboard must be at reachable point for easily operation. from that point to Split AC,empty conduit + necessary bends must in concealed mode by ele. contractor. THE ENCLOSURE SHOULD BE SAME MAKE AS MCB MAKE.	10	nos		
В	LIGHTING FIXTURES: (NOTE: ANY OF FIXTURES AND FITINGS SHALL BE RE- CONFIRMED WITH THE ARCHITECTS / CONSULANTS BEFOTE ORDERING THEM.				

Page 2 of 12

PRIC	PRICE BID FOR ELECTRICAL WORK OF SBI SIDHPUR BRANCH AT SIDHPUR.							
Sr. No.	DESCRIPTION	OTY	UNIT	RATE	AMOUNT			
3	Supply, installation, testing and commissioning (including supply and fixing flexible wires from holder to fixtures hardwares etc.) of The LED lamps should be of same make as fixture make The marking & cutting of fixtures should be in ele. contractor's scope fixtures should be approved by bank's ele. engineer / ele. consultant / architect. from the given make list before installations. LM 79 & LM 80 test reports to be submited. nichia / LUmileds / cree - LED should be used by manufacture. Lighting Luminaire of LED for Office single piece die cost aluminium M24 housing complete with driver unit, mirror optic and other accessories Lamps of about 100 lumen/W injection moulded PC diffusers with high brightness complete unit complying with international standard (LU49, LH801) - opertive on 190V - 270 V 50 Hz with Mini 3 years warranty complete with mounting stystem and lamp dully wired and tested Details as under.							

Page 3 of 12

AMOUNT

PRICE BID FOR ELECTRICAL WORK OF SBI SIDHPUR BRANCH AT SIDHPUR					
Sr. No.	DESCRIPTION	QTY	UNIT	RATE	AMOUNT
3.8	SITC of Decoretive 7 W (180 lumens) LED DOWN LIGHT PANEL with its driver also. (wipro make or philips / orient or equivalent co. make). (Approved by Architrct) (This is for down lighter in ACP work near entrance).	4	nos		
С	COMPUTER POWER SUPPLY & NETWORKING - TELE. SYSTEM.: Phase wire must be Yellow colour for UPS O/P DB, Red colour for PDB, Neutral Wire of Black colour & Green Wire for Earthing. Color code must be maintained. Tagging from DB MCB and Switch board must be done.				
4	SITC of 2 nos. of 6 A, 5 pin Sockets and 1 no. of 6 \ 16 A socket below table outlets with one 16 A switche with indicator Computer power supply with concealed company made metallic boxes or PVC flush box on walls / furniture's / trunking etc complete all respect with necessory wiring of mains of 2 no of 2.5 sq mm and 1 no of 1.5 sqmm pvc insulated copper conductor multi-stranded flexible wire with 20/25 dia. PVC conduits with accessories duly burried under floor with necessary chasing / breaking in floor and to be refinished with all necessary civil material etc. complete from UPSDB to Computer power supply boards.{Maxi. 3 computers in one circuit}. complete with necessary termination etc. complete.[White Colour Outer Plate For These Switchboards]. LOOP POINTS MUST BE OF SAME SIZED WIRES. Phase wire must be Red colour, Nutral Wire must be Black color & Green Wire for Earthing. Color code must be maintained. Tagging from UPS O/P DB MCB and Switch board must be done.	30	nos		
5	SITC of 2 nos. of 6 A, 5 pin Sockets and 1 no. of with one 6 A switches raw power supply with concealed company made metallic boxes or PVC flush box on walls / furniture's / trunking etc complete all respect with necessory wiring of mains of 2 no of 2.5 sq mm and 1 no of 1.5 sqmm pvc insulated copper conductor multi-stranded flexible wire with 20/25 dia. PVC conduits with accessories duly burried under floor with necessary chasing / breaking in floor and to be refinished with all necessary civil material etc. complete from PDB to Computer power supply boards.{Maxi. 3 Raw Power Points in one circuit}. complete with necessary termination etc. complete [Black Colour Outer Plate For These Switchboards].LOOP POINTS MUST BE OF SAME SIZED WIRES. Phase wire must be Red colour, Nutral Wire must be Black color & Green Wire for Earthing. Color code must be maintained. Tagging from PDB MCB and Switch board must be done.	16	nos		
6	SITC of CAT 6 UTP pvc insulated copper conductor data cable of D - Link with 20/25 dia. PVC conduits with accessories duly burried under floor with necessary chasing / breaking in floor and to be refinished with all necessary civil material etc. or to be cleated on wall / ceiling with saddles / spacer etc. necessary termination etc. with ferrule numbering at both ends of each piece of cable complete. [2 Lines from BSNL Krone to new krone in server room].	40	mtr		

PRIC	CE BID FOR ELECTRICAL WORK OF SBI SIDHPUR	BRA	NCH	AT SIE	HPUR.
Sr. No.	DESCRIPTION	QTY	UNIT	RATE	AMOUNT
7	SITC of CAT 6, RJ 45 information outlet (I/O) of D-link mke with front modular cover plate, flush box metallic or PVC for trucking system etc. complete with terminations etc complete.with Providing, installing, testing, commissioning of CAT 6 UTP pvc insulated copper conductor data cable of D-link make with 20/25 dia. PVC conduits with accessories duly burried under floor with necessary chasing / breaking in floor and to be refinished with all necessary civil material etc. or to be cleated on wall / ceiling with saddles / spacer etc. necessary termination etc. with ferrule numbering at both ends of each of piece of cable etc. complete as per the requirement from data rack to I/O points below tables. etc. (One for LCD & Two for ATM & one for IP phone in BM cabin). Dual jack plate will not be allowed. Cross Ferruling need to be provided for each point. on Data point tagging must be done).	30	nos		
8	SITC of 12 U metal rack for computer clamping switch etc complete with Tray Mounting Fan + power supply board. Bank's hardware - port switch / patch panel must be installed by ele. Contractor in this rack (make : D Link / Digi Link / Elixer).	1	nos		
9	SITC of 24 port patch panel for computers mounting in metal rack. (make: D Link/Digi Link).	2	nos		
10	SITC of the Patch cord 1 mtr. Long (factory built)When supplying , then first ask to BM / Consultant / Architect / Bank Authority.	33	nos		
11	SITC of the Patch cord 2 mtr. Long (factory built)When supplying , then first ask to BM / Consultant / Architect / Bank Authority.	31	nos		
12	SITC of telephone point with Telephine socket outlets of RJ 11 of aapproved make with company made concealed boxes in walls / furniture's etc. complete with Providing, installing, testing, commissioning of 2 pair of 0.51 cross section pvc insulated copper conductor telephone wire of ITI approved with 20/25 dia. PVC conduits with accessories duly burried under floor with necessary chasing / breaking in floor and to be refinished with all necessary civil material etc. or to be cleated on wall / ceiling with saddles / spacer etc. necessary termination etc. complete.from krone box to tele. RJ - 11 sockets below tables. etc for Intercom/fax/direct Tele. facility. Cross Ferruling need to be provided for each point. on Telephone point tagging must be done.	15	nos		
12 (A)	SITC of 20 pair krone telephone tag block duly enclosed in sheet metal powder coated box with locking arrangement complete with necessary terminations.	1	nos		
D	DISTRIBUTION BOARD AND PANELS :				
13	Supply, installing, testing and commissioning of metallic double door type distribution board with all necessary connection complete to be installed concealed in wall / surface mount complete to the satisfaction of the Engineer in charge. The DB should be of same make as MCB make.				
13.1	6 - WAY TPN DB: (LDB). All MCB should be 'B' type.	1	nos		

Sr. No.	DESCRIPTION	QTY	UNIT	RATE	AMOUN
	incoming: 40 A FP MCB - 1 NO.				
	outgoing : 25 A DP ELCB, 100 mA - 3 NO . outgoing : 6 to 20 A SP MCB (10 nos).				
	outgoing : 6 to 20 A 51 MCb (10 nos).				
13.2	6 - WAY TPN DB : (PDB). All MCB should be ' C ' type.	1	nos		
	incoming: 40 A FP MCB - 1 NO.				
	outgoing : 25 A DP ELCB, 100 mA - 3 NO.				
	outgoing : 6 to 20 A SP MCB (12 nos).				
13.3	6- WAY TPN DB INCOMER (4+4) : (ACDB). All MCB should be 'C' type.	1	nos		
	incoming : 63 A FP MCB - 1 NO . outgoing : 20 A / 25 A DP MCB (10 nos) for HI- WALL SPLIT AC points.				
42.4	12 WAY SPN DB: (UPS DB) OUTPUT BRANCH All MCBs must be				
13.4	C Type Characteristic.	2	nos		
	incoming : 63 A DP 100 mA ELCB.				
	outgoing : 10 to 20 A SP MCB (8 nos).				
13.5	8 - WAY SPN DB : (ATMDB). All MCB should be ' C ' type.	1	nos		
	incoming : 40 A FP MCB - 1 NO .				
	outgoing : 20 A / 25 A DP MCB (1 nos) for HI- WALL SPLIT AC				
	outgoing : 10 A SP MCB (1 nos) - Raw power pts				
	outgoing : 10 to 20 A SP MCB (1 nos) ATM lighting SB.				
13.6	4 WAY SPN DB. (For essential ups points - UPS O/P DB.).	1	nos		
	outgoing: 25 A. DP MCB - 1 NO FOR UPS OUTPUT.				
	outgoing : 10 A / 20 A. SP MCB - 2 NO FOR essential ups points - DATA RACK / FIRE PANEL / CCTV NVR PTS.				
13.7	4 WAY SPN DB. (For ATM ups points - UPS O/P DB - in ATM AREA.).	1	nos		
	outgoing : 25 A. DP MCB - 1 NO FOR UPS OUTPUT.				
	outgoing : 10 A / 20 A. SP MCB - 2 Nos.				
13.8	4 WAY SPN DB. (For UPS O/P DB - BRANCH AT UPS ROOM).	1	nos		
	outgoing: 40 A. DP MCB - 1 NO FOR UPS OUTPUT.				
	outgoing : 25 A. DP MCB - 1 NO FOR UPS OUTPUT.				
13.9	DP MCB METAL ENCLOSURE DB . (For UPS O/P DB - FOR ELOBBY AT UPS ROOM).	1	nos		
	outgoing : 25 A. DP MCB - 1 NO FOR UPS OUTPUT.				
	UPS 12 WAY SPN DB. (UPS I/P DB) All MCBs must be C Type				
13.10	Characteristic.	1	nos		
	incoming: 63 A FP MCB - 1 NO FOR 3 - phase UPS.(big).				
	outgoing: 25 A DP MCB - 1 NO FOR 1 - phase UPS.				
	outgoing: 10 A SP MCB - 1 NO FOR UPS ROOM LIGHTING.				

Page 7 of 12

Sr. No.	DESCRIPTION	QTY	UNIT	RATE	AMOUN'
14	SITC of 25 A FP changeover switch - mcb type (C - Curve) with powder coated compny made metallic double door sheet stell enclosure complete for inverter supply to LDB - check SLD. THE ENCLOSURE SHOULD BE SAME MAKE AS MCB MAKE.	1	nos		
15	SITC of Main panels as per drawing and specifications. Panel should be dust and vermin proof. Panel shall be fabricated from 14/16 SWG CRCA sheet metal duly powder coated of approved paints. Panel should be as per the sepecifications of ERDA/CPRI. fabrication, Switch gear installation. Internal wiring and Test Certificate from Manufacturer to be submitted All MCBs must be C Type Characteristic. Panel Drawing Need to be approved by Electrical Consultanat / Bank's Engineer before starting work. READ SLD CARFULLY.				
	MAIN PANEL:	1	nos		
	Incoming feeder: 160 AMP ON LOAD CHANGE OVER SWITCH L&T MAKE (MANUAL CHANGE OVER SWITCH) Incoming feeder: 125 A C&S / L&T MCCB Make CSE1N80ETM4P-80A (1 No.). REGULAR POWER. Incoming feeder: 80 A C&S / L&T MCCB Make CSE1N80ETM4P-80A (1 No.). ESSENTIAL POWER. * 63 A, FP Change over switch (1 No.). REGULAR POWER. * 63 A, FP Change over switch (1 No.). ESSENTIAL POWER. * 160 AMP. 500 Volts, 3 phase 50 Hz FP Alu. bus bars of suitable length - Current ratio shall be 1 sq mm = 1.2 A. * 80 AMP. 500 Volts, 3 phase 50 Hz FP Alu. bus bars of suitable length - Current ratio shall be 1 sq mm = 1.2 A. * 63 AMP. 500 Volts, 3 phase 50 Hz FP Alu. bus bars of suitable length - Current ratio shall be 1 sq mm = 1.2 A. * Oligital AVF Meter with control fuses. C.T. shall be of 15VA class 1 type and shall be resin cast type. * Outgoing feeder: * Timer of L & T make Cat. No. 67DDTO digicom Timer with 16A. 4P contactor / Theben make Cat no. SUL 180 a - T180 0 001 ANALOG Timer with L & T make contactor MNX 18 (operating coil voltage 230V, 50 Hz). (24 hrs) 1 No for signage light. * 25 A DP MCB (1 no - Sign board for branch).				
	* 40 A FP MCB (1 NO - LDB). * 40 A FP MCB (1 NO - DB). * 40 A FP MCB (1 NO - PDB). * 63 A FP MCB (1 NO - UPSDB). * 40 A FP MCB (1 NO - ATMDB).				
	* 63 A FP MCB (1 NO - ACDB).				
	* 40 A FP MCB (1 NO - SPARE DB).				

Page 8 of 12

PRIC	CE BID FOR ELECTRICAL WORK OF SBI SIDHPUR	BRA	NCH	AT SIE	HPUR.
Sr. No.	DESCRIPTION	QTY	UNIT	RATE	AMOUNT
16	SITC of 160A FP MCCB- L&T D sine CM90642OOMO (25KA) (1 No.) with Sprader terminal (Ics =100% Icu., confirmed to IS / IEC 60947 - 2 adujstable Ir rating from 0.7 to 1) Unit M. S. compartment enclosure IP65 with hinged door & locking arrangement duly fabricated from 18 SWG sheet metal box duly painted with one coat of red-oxide paint and two coats of approved enamell paints with 100A OPEN TYPE FP MCCB UNIT with Phase indicator lamps phase wise, control fuses & wooden back complete. THIS WILL BE INSTALLED NEAR MAIN DOOR - INSIDE OR OUTSIDE - OF THE BANK. (first ask to BM / Consultant / Architect / Bank Authority.	1	nos		
Е	EARTHING SYSTEM:				
17	Providing and making Earthing Pit with all necessary matterial and making masonry kundi, watering arrangment etc complete as per ISI 3043-1987 (FOLLOWING ITEMS MAY OPERATE). Resistivity as per IEC / IS. (3 years Manufacturer Warranty. Earthing Certificate Need to Attached). (At the Time of buried of earthing Photograph must be taken Without Photographic Proof Earthing Will be Rejected. Earthing Rod Photo Must be attached with Bill.). Earthing need to measure at Site and it should be less than 5 Ohm. If found more than 5 ohm than will be rejected. Earthing Pit Must be Provided for both Cu as well as GI earthpit.				
17.1	ECO SAFE environment friendly electrical grounding system with T-193-Hot Dip Galvanised, having 50mm dia. of outer pipe and 25 mm dia. of inner pipe and length of 3mtrs with 50kg Back Fill Compound as per UL 476, of Powerfill Eco friendly electrical grounding backfill compound and clamp (DB - PANEL) - G. I(Chemical GI Earthing) ERDA & NSIC approved, E link or ETP MAKE or ASHLOK MAKE. Any other make will not be consider. (DB - PANEL) .	1	nos		
17.2	ECO SAFE environment friendly electrical grounding system with T-193-Copper electrode used upto 11 KV, having 50mm dia. of outer pipe and 25 mm dia. of inner pipe and length of 3mtrs with 50kg Back Fill Compound as per UL 476, of Powerfill Eco friendly electrical grounding backfill compound and clamp (UPS) - Chemical GI Earthing) ERDA & NSIC approved, E link or ETP MAKE or ASHLOK MAKE. Any other make will not be consider Cu. (UPS).	1	nos		
18	Supply, laying and jointing of following wire / strip / earth cable on walls, ceiling etc. With necessary non rusting clamps, washers, nuts and bolts etc complete.				
18.1	25 x 3 mm G.I. Strip - From G. I. Earthpit to Main Panel + From Cu. Earthpit to UPS I / P DB.	50	Rmt		
18.2	8 SWG G.I. Wire with 20 mm dia. PVC rigid conduit duly cleated / concealed / burried in floor etc. complete for ELE. PANEL, ALL DBS , ETC.	30	Rmt		
18.3	8 SWG CU. Wire with 20 mm dia. PVC rigid conduit duly cleated / concealed / burried in floor etc. complete.	60	Rmt		
F	CABLES & CABLE TERMINATIONS:				

Page 9 of 12

PRIC	CE BID FOR ELECTRICAL WORK OF SBI SIDHPUR	BRA	NCH	AT SIE	HPUR.
Sr. No.	DESCRIPTION	QTY	UNIT	RATE	AMOUNT
19	Supply, Lying, installation, testing and commissionig of following sizes of PVC insulated PVC sheathed copper / aluminum conductor armoured cable to be laying in existing cable trench or to be laid in existing pipes of with necessary clamps, spacers with cleating on wall ceilling etc. complete to the satisfaction of EIC. All types of cable excavation works should be in contractor's scope.(LENTH TO BE VERIFY AT SITE) with end termination of following PVC insulated armoured cables incluming supply and fixing of brass single compression type cable glands and crimping type aluminum / copper lugs suitable for terminations of armoured cables of following overall diameters, incl.				
19.1	3 C x 2.5 sq. mm Cu . Conductor YWY cable. (for Signboard).	15	mtr		
19.3	4~C~x~6.0~sq. mm Cu. Conductor YWY cable. (Main Panel to UPS I/P DB) .	45	mtr		
19.4	$4~{\rm C}~{\rm x}~10.0~{\rm sq.}$ mm Cu. Conductor YWY cable. (Main Panel to $3~{\rm PHASE}$ ACDB) .	5	mtr		
19.5	$4\ C\ x\ 16.0\ sq\ mm$ Alu. Conductor AYFY cable. (Main Panel to LDB, PDB , ATM DB) .	20	mtr		
19.6	3.5~C~x~35.0~sq. mm Alu. Conductor AYFY cable. (DG cable from Panel to DG set) (LENGTH as per site contition) .	20	mtr		
19.7	$3.5~\rm{C}~x~50.0~sq.$ mm Alu. Condudtor AYFY cable. (main cable from Panel to main mccb nr. energy meter) (LENGTH as per site contition) .	30	mtr		
19.8	25.0 sq. mm single core Cu. wire supply & laying for main load wire from meter to main switch in flexible pipe.	8	mtr		
10.9	3 C X 6.0 sq. mm Cu. armoured cable with 20 mm/25 mm dia PVC rigid conduits 1.5 mm thick ISI mark . (UPS to UPS O/P DB & UPS I/P DB to UPS) for branch.	30	mtr		
19.10	3 C X 4.0 sq. mm Cu. armoured cable with 20 mm/25 mm dia PVC rigid conduits 1.5 mm thick ISI mark . (UPS O/P DB IN UPS ROOM to UPS O/P DB & UPS I/P DB to UPS + UPS O/P DB IN UPS ROOM TO ESSENTIAL UPS O/P DB.).	20	mtr		
19.11	SITC OF HDMI CABLE FOR DISPLAY	15	mtr		
G	MISCELLANEOUS ITEMS :				
20	Supply and installation of 300 x 300 x 40 mm size GI box duly fabricated from 18 SWG m.s. sheet with top cover of s. s. sheet complete with necessary knock outs at all the sides of box for conduit entries duly fixed in floor, including breaking in floor and re-finished the same etc. complete (Wire Draw Box).	10	nos		
21	Supply and installation of 150 x 150 x 40 mm size GI box duly fabricated from 18 SWG m.s. sheet with top cover of s. s. sheet complete with necessary knock outs at all the sides of box for conduit entries duly fixed in floor, including breaking in floor and re-finished the same etc. complete (Wire Draw Box).	17	nos		
21	necessary knock outs at all the sides of box for conduit entries duly fixed in floor, including breaking in floor and re-finished the same etc.	17	nos		

Page 10 of 12

PRI	CE BID FOR ELECTRICAL WORK OF SBI SIDHPUR	BRA	NCH	AT SII	OHPUR.
Sr. No.	DESCRIPTION	QTY	UNIT	RATE	AMOUNT
22	Supply and installation of 2.5 sq. mm. 3 core flexible cable of approved make (3 mtr. Length) with heavy duty industrial pvc flexible pipe & 15 amp. 3 pin top of approved make for the supply of locker room.	3	nos		
23	SITC of 24 Hr, 7 days A/C timer with 2 nos of TP power contactor of M.D.S, L & T , SEIMENS, THEBEN (indoasian) Make. All enclosed in sheet steel powder coated enclosure of 200 X 200 mm complete with all necessary termination for e lobby AC supply. Here Ready made Cyclic Timer Will not be permited to be installed in UPS ROOM	1	nos		
24	SITC of CABLE TV cable line with proper fixing and connecting with modular Co-Axial TV Socket 2 run.	30	mtr		
25	Supply & laying of the empty conduit 25 mm.	60	mtr		
26	Supply & laying of the empty conduit 40 mm. used for GI strip in flooring at GF .	50	mtr		
27	Laisioning work (addition Load) WITH Electric suppply Co. in branch & Apporoval and Neccessary cirtificate.	1	job		
28	Removal of old wiring in area which will be proposed to be redesigned & providing Necessary plug points & light points for tube lights (including necessry wiring) at various locations as required by various contractors for execution of various works / to run equipments such as drill / cutter etc. during the entire execution process. The accessaories used for this purpose shall be of temp. nature (anchor piano or eq.) & the contractor has to take back the same on completion of the project. The supply for this shall be taken from the temporary connection provided at / from nearby general meter under co.ordintion with the LANDLORD. & also providing temporary power supply for computers and data connection for computers with wiring, switchboard, Comp. I/O Points,etc. for smoothly running of the branch with removing & reshifting of the computers , printers, etc. bank hardware accessories.	1	job		
	TOTAL - PART A :::				
,	PART - B :::: BUYBACK				
1	BUY BACK: FROM premises - Entire existing electrification, telephone wirings, LAN wirings with conduits shall be removed and shall be purchased by the contractor including switches and accessories, lighting fixtures, ceiling fans, exhaust fan , Cables, etc(Contractor shall last visit site before quoting and the submit the list of material with quantities which are buying and the quoted rate shall be lump sump basis)	1	Job		
	TOTAL - PART A - PART B (BUYBACK) ::::				
	GRAND TOTAL :::				
1	ALL RATES SHOULD BE INCLUDE OF ALL TAXES EXCLUDING GS'	T WHAT	EVER	IS APPLI	CABLE.

PRICE BID FOR ELECTRICAL WORK OF SBI SIDHPUR BRANCH AT SIDHPUR.							
Sr. No.	DESCRIPTION	OTY	LINIT	RATE	AMOUNT		
		~					
2	THE CONTRACTOR SHOULD DEPUTE ONE PERSON AT SITE FROM S		F WORI	K TO FINI	SH FOR		
3	THE CONTRACTOR SHOULD WORK ACCORDING TO THE FINAL LA		DANIIC	CENCINI	EED / ELE		
5	THE CONTRACTOR SHOULD SUBMIT & APPROVE MAKE LIST WITH THE CONTRACTOR SHOULD CHECK ELE. APPROVED MAKE LIST BE			S ENGIN.	EEK / ELE.		
6	THE CONTRACTOR SHOULD CHECK ELE. AFFROVED MAKE LIST BE			DI III DED	AC DED		
7	LOWEST BIDDER SHALL BE DECIDED AFTER DEDUCTING THE BUYE			DUILDER	ASPER		
8	THE CONTRACTOR SHOULD SUBMIT BANK GUARANTEE OR WARR			IDEC IE	D EOP		
9	CONTRACTOR SHOULD SUBMITTED THE CERTIFICATE OF WIRES						
10	EARTH RESISTANCE SHOULD BE CHECKED & SUBMITTED THE REPO						
11	SINGLE LINE DIAGRAM SHOULD BE SUBMITTED AT BRANCH & ON						
12	SHOCK TREATMENT CHART SHOULD BE PEST NEAR DB / MAIN PA						
13	THE CONTRACTOR'S PRESENCE MUST BE COMPULSORY FOR SHIFT						
13	CONFIRMATION/ RECEIVED SIGNATURE FROM BRANCH MANAGE						
14	PATCH CORDS.						
15	THE RATES QUOTED BY THE CONTRACTOR IN THE COLUMN WHER	PEOLIAN	JTITV A	2- LINIT A	DE NOT		
16	THE CONTRACTOR SHOULD BE ADVISED NOT TO LAY ANY CONDU						
17	IF THE CONTRACTOR HAS NOT CARRIED OUT ELECTRICAL WORK				<u> </u>		
18	THE CONTRACTOR SHOULD BE ADVISED TO FIX 2 / 3 INCH SIZE PIE				DE AREA		
10	THE CONTRICTOR OFFICED BE THE VIOLED TO THE 2 / 3 INVESTIGATE THE	DI OKI	ICELO I	11 00 1011	JE / IKE/		
		Sign & S	Seal wit	h the Cont	ractor		
		0					

Page 12 of 12