

RENOVATION OF JALUKE BRANCH
BOQ for Electrical Installation Works

SL No	DESCRIPTION	UOM	QTY	Rate (Rs.) (Exclusive of GST on work contract)	Amount (Rs.) (Exclusive of GST on work contract)
1	<p>Capacitor Panel: Supply and installation of 30 KVAR APFC panel, floor/wall mounted front operated totally enclosed vermin proof, indoor non-drawout-cubicle type power panel fabricated out of 16 SWG thick CRCA sheet having gasketed hinged cover on each cubicle fully powder coated with suitable bus bar for connecting the contactors, MCB's, Capacitors, etc with the following accessories A set of R-Y-B LED indicating lamp at incomer</p> <p>63A, TPN MCCB, 35kA as incomer - 1No 2 No. A 3P contactor for 10 KVAR, 1 Nos. 32A 3P contactor for 5 KVAR, 2 Nos, 25A, 3P contactor for 2 KVAR and 1 No, 16A, 3P contactor for 1 KVAR 2 No. 10 KVAR, 1 Nos. 5 KVAR, 2 Nos. 2 KVAR and 1 No. 1 KVAR. 1 no. 6-step APFC relay of minimum size 150 MM X 150 MM suitable for above arrangement ON/OFF push button for each capacitor ON/OFF LED type indication lamp for each capacitor</p>		1		
2	Sub-main line:- Wiring in MS conduit of IS specification of Proper size with core PVC insulated stranded copper wire 11KV grade (Finolex/Havells/Polycab/ RR Kabel/ Richa/KEI or equivalent) and with supply ,installation, commissioning of all the materials required including proper termination,connection in complete as required from main DB to various DBs:-				
i)	with 3nos 4sq.mm (1ECC)	RM	160		
ii)	with 3nos 6sq.mm (1ECC)	RM	120		
3	Supply ,installation ,testing and commissioning of distribution board manufactures made sheet steel enclosure With the following MCBs (DB,MCB and MCCB Make- Legrands/ Havells/ L&T/ SIEMENS or equivalent) and connecting the same to the system.				
i)	Computer/Raw power DB, SPN double door with 40A (30mA)DP RCCB as incomer & 5nos 10A SP MCB as outgoing.	No.s	3		
ii)	DB with 32A DP MCB.	No.s	4		
iii)	DB with 16A DP MCB, (Security and fire)	No.s	2		
iv)	DB with 32A DP RCCB.	No.s	6		
v)	DB with 32A MCB Changeover	Nos.	1		
vi)	VTPN Double Door Distribution Board with 125 A 4 Pole MCCB (36kA) as incomer and 8 Nos. 32A SP MCB's at outgoing (AC)	Set	1		
vii)	VTPN Double Door Distribution Board with 125A 4 Pole MCCB (36kA) as incomer and 1 No. of 63A TP MCB , 4 nos. of 40 A SP MCB, 2 Nos. of 32A MCB and 2 nos of 16A SP MCB at out going	Set	1		
viii)	Light DB SPN double door with 40A (30mA)DP RCCB as incomer & 5 nos 10A SP MCB as outgoing.	No.s	3		
4	Supplying, installing and commissioning of PVC Armored cable complete with proper cable glands and two nos. of 8SWG GI wire (Havell's/Richa/RR kebel/KEI or equivalent) alongwith all the other materials required including proper connection in complete as required from main Panel,Power Distribution Board to various DBs .				

SL No	DESCRIPTION	UOM	QTY	Rate (Rs.) (Exclusive of GST on work contract)	Amount (Rs.) (Exclusive of GST on work contract)
i)	With 3.5 core x 35 sq. mm cable	RM	80		
ii)	With 3.5 core x 70 sq. mm cable	RM	38		
5	Supply, installing and commissioning of earth station including digging and refilling back the pit with black soil and with 3.15mm x300mm size copper plate duly tinned through out the surface of the plate, placed at least 1.5Mtr,below the ground level with 2nos 10sq.mm PVC insulated stranded copper conductor in 20mm GI pipe, fixed to the plate and providing 40mm,2mtr,long GI pipe with reducer and funnel at top for watering pipe with supplying and laying earth continuity wire of 2x10sq.mm copper stranded PVC green color in heavy duty MS conduit on the wall from earth plate to starting point of the line earth connector with proper earth pit.	Nos.	5		
	i) Supplying and fixing 25x3 mm copper strip, insulated by heat pressurized heavy gauge PVC sleeve, duly jointed by full lap brazing and drawn underground in 40 mm class B GI pipe from the inspection pit to the inside of the branch premises.	RM	40		
	ii)Supplying and fixing 2X8 SWG dia copper earth wire in PVC conduit on surface or in recess for loop earthing from panel to DB	RM	90		
6	Computer/Raw Power point wiring in MS conduit of IS specification of proper size with 3nos 2.5sq.mm single core PVC insulated stranded copper wire 1.1KV grade(Finolex/Havells/Polycab/ RR Kabel/ Richa/KEI or equivalent) and with all material supply installation and commissioning complete from /PDB(Raw) .The wiring shall be carried out on surface above false ceiling by chiseling the existing surface and plastering the same with cement etc. after fixing the MS conduit with all accessories like saddles screws, bends T-joint etc. 2 coats of painting Matching to the surface including supply installing, testing, commissioning of modular plate type switch and socket (Legrands / MK or equivalent) for computer terminal on sheet steel enclosure (cadmium plated),duly fitted with screw to the steel conduit and fixed to the wall partition furniture with all interconnection and proper earthing .All the opening shall be covered with blank plate and be sealed to make the box vermin proof.B48(maximum three points in single circuit)				
i)	With 3nos 6A socket with single 16A switch.	No.s	19		
ii)	With 2nos 16A socket with individual switch.	No.s	15		
iii)	With 1nos 16A socket with individual switch.	No.s	5		
7	Supply, installation testing and commissioning of recessed mounted circular LED downlighter with 15W LED lamp. Make :- Bajaj/Havels/Phillips/Wipro/Crompton or equivalent. (Model: Havells INTEGRANXTDLR15WLED857S TR or Equivalent specification)	Nos	34		
8	Supply, installation testing and commissioning of surface mounted circular LED downlighter with 15W LED lamp. Make :- Bajaj/Havels/Phillips/Wipro/Crompton or equivalent. (Model: Havells GLOWDLS15WLED830S or Equivalent Specification)	Nos	8		
9	Supply, installation testing and commissioning of recessed type LED luminaire with complete PMMA Difuser with 36 W LED lamp (size 2"X 2")(Model:Plano or equivalent) . Make : Bajaj/ Havels/ Phillips/ Wipro/ Crompton or equivalent	Nos	18		

SL No	DESCRIPTION	UOM	QTY	Rate (Rs.) (Exclusive of GST on work contract)	Amount (Rs.) (Exclusive of GST on work contract)
10	Supply installation testing and commissioning of LED batten Single Tube light fittings with 20W (Model: Havells LUMILINEBS20WLED865SPCWH or equivalent Specification) with glare free light distribution wall mounted at ceiling/false ceiling level/. Make :- Bajaj/ Havels/ Phillips/ Wipro/ Crompton or equivalent	Nos	16		
11	Supply and installation of Wall Mounted fan 400 mm full Metallic body and metallic Blade, 1400 rpm crompton/ bajaj/ usha/ orient make	No.s	4		
12	Supply and installation of Ceiling fan 1200 mm crompton/ bajaj/ usha/ havells make	No.s	2		
13	Supply and installation of heavy duty Exhaust Fan 300 mm crompton/ bajaj/ usha/ havells make	No.s	5		
14	Supplying, installation,testing & commissioning of Security ligh with 25W LED lamps with pressure die cast housing with epoxy coated dark graphite grey colour finish and prismatic polycarbonates cover with individual LED lenses, including necessary GI bracket with clamp. Make :- Bajaj/ Havels/ Phillips/ Wipro/ Crompton or equivalent	Nos.	4		
15	Supply and installation of 10 Meter roll 55W, IP20 Flexible LED Strip surface mounted alongwith required LED Driver as back lighting. Havells or equivalent make.	No.s	10		
16	Wiring for light/fan/exhaust fan points using 3 X 1.5 1.1 kV grade PVC insulated stranded copper conductor wire (Finolex/ Havell's/ Richa/ RR kebel/ KEI or equivalent) for phase, neutral and earth in 25 mm dia heavy duty MS conduit along with associated accessories like MS junction boxes, bends, saddles, screws et. concealed in wall, floor, under flooring, below false ceiling or on surface as well as suspended from ceiling with 25mm X 3 mm MS flat suspenders duly painted above false ceiling from individual light/Fan/Exhaust Fan point outlet. etc. to individual modular type switch boards, 10 Amp modular plate type switches etc.(MK/Legrand's/Havel's or equivalent), as required complete including circuit wiring with 3 X 2.5 sqmm. 1.1 kV grade PVC insulated stranded copper conductor wire and as per site requirement and as instructed by SBIIIMS Engineer.				
i)	Light/fan point (Two downlighter/ 2"X 2" rececced light fittings to be connected through one point)	No.s	35		
ii)	Light/fan point (four downlighter/ two 2"X 2" rececced light fittings to be connected through one point)		20		
iii)	6A socket & switch at same board	No.s	8		
iv)	Fan Point with electronic modular type regulator.	No.s	2		
v)	16A, 5 pin industrail plug & Socket with 25 A MCB protected (for Safe room & Record room)	Nos.	2		
vi)	Modular type with 6A SP MCB for Exhaust fan and wall fan	No.s	12		
	Total				

GST on work contract will be extra as applicable.